

EVERYTHING 4 LESS



ENJOY YOUR BOOKS



PLEASE VISIT OUR STORE FOR EVEN MORE GREAT STUFF!

WWW.EVERYTHING4LESSSTORE.COM

COPYRIGHT NOTICE

ALL MATERIALS INCLUDING CD/DVD AND PDF FILES ARE COPYRIGHTED

WWW.EVERYTHING4LESSSTORE.COM VON WALTHOUR PRODUCTIONS AND MAY NOT BE REPRODUCED, COPIED OR RESOLD UNDER ANY CIRCUMSTANCES. YOU MAY HOWEVER MAKE A COPY FOR YOUR OWN PERSONAL BACKUP. MATERIALS ARE FOR PERSONAL USE ONLY.

IF YOU PURCHASED THIS FROM ANYWHERE BUT FROM US PLEASE NOTIFY US IMMEDIATELY SO THAT WE MAY CHECK IF YOU PURCHASED FROM AN AUTHORIZED RESELLER SO WE CAN LET YOU KNOW IF YOU NEED TO RETURN FOR FULL REFUND FROM AN UNAUTHORIZED SELLER.

THANKS AGAIN AND PLEASE TAKE THE TIME TO VISIT OUR STORE.

ATTENTION! EVERYTHING ON SALE NOW!!



HOT SALE!

**THIS PAGE COPYRIGHT VON WALTHOUR PRODUCTIONS
WWW.EVERYTHING4LESSSTORE.COM**

AMERICAN LOCTAL 4, 5, 6 & 7 PIN BASE TYPE TUBES

00A	5.0	JR-3200-0	33	28	P4	420	666	
01A	5.0	JR-3200-0	48	32	P4	455	725	
0A1	5.0	JR-3200-0	48	32	P4	455	725	
1A4P	2.0	JR-0230-0	29	33	P4	470	750	Cap = G
1A6	2.0	JR-0250-4	35	35	P4	470	750	Pent. Sect. Cap = G
1A6	2.0	JR-4350-2	35	73	P4		150	MICROMHOS ONLY OK OVER 120 ON 3000 SCALE
1AB5	1.1	JR-6230-0	0	61	P4	880	1400	Cap = G
1B4P	2.0	JR-0230-0	20	45	P4	630	1000	TRIODE SECT. MICROMHOS ONLY. OK OVER 200 ON 3000 SCALE
1B5	2.0	JR-5200-0	28	73	P4		475	Diode No. 1
1B5	2.0	JR-5400-0	28	0	P1*			Diode No. 2
1B5	2.0	JR-5300-0	28	0	P1*			Ampl. Sect. Cap = G
1C6	2.0	JR-0253-4	29	24	P4	410	650	MICROMHOS ONLY OK OVER 240 ON 3000 SCALE
1C6	2.0	JR-4352-0	50	73	P4		300	Cap = G
1D5	2.0	JR-0340-0	29	33	P4	470	750	
1F4	2.0	JR-3240-0	23	62	P4	880	1400	
1L4	1.5	HT-6210-0	19	52	P4	645	1025	
1LA4	1.5	JR-6230-0	43	39	P4	505	800	Pent. Sect.
1LA6	1.5	JR-6253-4	24	39	P4	505	800	Osc. Sect. MICROMHOS ONLY OK OVER 240 ON 3000 SCALE
1LA6	1.5	JR-4352-6	46	73	P4		300	Heptode Sect. ENG. ONLY OK OVER 300 ON 3000 SCALE
1LB4	1.5	JR-6230-0	51	44	P4	580	925	Osc. Sect.
1LB6	1.5	JR-6243-7	0	0	P4		400	Pent. Sect. OSC. SECT. MICROMHOS ONLY OK OVER 240 ON 3000 SCALE
1LB6	1.5	JR-6357-4	20	55	P4	945	1500	Pent. Sect.
1LC5	1.5	JR-6234-0	29	37	P4	490	775	Diode Sect.
1LC6	1.5	JR-6253-4	30	25	P4	440	700	
1LC6	1.5	JR-4352-6	30		P4		300	
1LD5	1.5	JR-6230-0	28	17	P4	380	600	
1LD5	1.5	JR-6430-0	28	0	P1*			
1LE3	1.5	JR-6205-0	0	61	P4	820	1300	
1LF3	1.5	JR-6205-0	20	57	P4	775	1200	
1LG5	1.5	JR-6234-0	25	50	P4	660	1050	
1LH4	1.5	JR-6200-0	16	73	P4		275	Triode Sect. MICROMHOS ONLY OK OVER 220 ON 3000 SCALE
1LH4	1.5	JR-6400-0	16	0	P1*			Diode Sect.
1LN5	1.5	JR-6234-0	11	34	P4	470	750	
1R4	1.5	JR-0407-0	0	0	P1*			Diode
1V	6.3	JR-0203-0	0	49	P3*			
2A3	2.5	JR-3200-0	67	82	P4	1890	3000	
2A5	2.5	JR-4235-0	29	73	P4	1260	2000	
2A6	2.5	JR-0205-0	11	34	P4	470	750	Triode Sect. Cap = G
2A6	2.5	JR-0405-0	11	0	P1*			Diode No. 1
2A6	2.5	JR-0305-0	11	0	P1*			Diode No. 2
2A7	2.5	JR-0236-5	22	50	P4	630	1000	Pent. Sect. Cap = G
2A7	2.5	JR-5436-0	30	73	P4		400	Osc. Sect. MICROMHOS ONLY OK OVER 220 ON 3000 SCALE

2AS15	2.0	JR-1534-0	Use this setting for short test only				SHORT ON 1, 4, 5. SET LIFE TEST SWITCH TO LIFE TEST
2AS15	2.0	JR-0500-0	0	0	P1*		OK IF NEEDLE APPROACHES 100 ON 3000 SCALE
2B3	1.5	JR-0000-0	0	60	P5*		Cap = P
2B4	2.5	JR-3204-0	#	91	P5*		OK ABOVE DIODES OK SHORT ON 1
2B6	2.5	JR-4236-0	15	60	P4	945 1500	Strikes at about 72
2B7	2.5	JR-0236-0	30	50	P4	630 1000	Pent. Sect. Cap = G
2B7	2.5	JR-0536-0	30	0	P1*		Diode No. 1
2B7	2.5	JR-0436-0	30	0	P1*		Diode No. 2
2B23	6.3	JR-0307-0	0	30	P2*		
2C21	6.3	JR-4506-0	38	62	P4	865 1375	Triode No. 1
2C21	6.3	JR-0302-0	38	62	P4	865 1375	Triode No. 2 Cap = G
2C45	7.5	JR-3200-0	37	76	P4	1385 2200	
2C50	12.6	JX-2103-0	41	69	P4	1135 1800	Triode No. 1
2C50	12.6	JX-4506-0	41	69	P4	1135 1800	Triode No. 2
2E5	2.5	JR-5403-0			P4		Eye Open
2E5	2.5	JR-5423-0			P4		Eye Closed
2E22	6.3	JR-3024-0	0	87	P4	2520 4000	Cap = P
2G5	2.5	JR-5403-0	0	0	P4		Eye Open
2G5	2.5	JR-5423-0	0	0	P4		Eye Closed
2V2	2.5	JR-0005-0	0	36	P5*		Cap = P. Short on 3
2X2A	2.5	JR-0000-0	0	73	P5*		Cap = P
2Z2	2.5	JR-0200-0	0	15	P3*		
3B7/1291	2.5	JR-6700-0	12	61	P4	945 1500	Triode No. 1
3B7/1291	2.5	JR-3200-0	25	61	P4	945 1500	Triode No. 2
3B24W	3.0	JR-0000-0	0	83	P5*		1st Half of Fil. Cap = P
3B24W	3.0	CR-0000-0	0	83	P5*		2nd Half of Fil. Cap = P
3B28	2.5	JR-0000-0	0	50	P3*		SEE NOTE AT END OF CHART
3B29	4.3	JR-0000-0	0	87	P5*		Cap = P
3C6/XXB	2.5	BY-5600-0	10	55	P4	695 1100	SEE NOTE AT END OF CHART
3C6/XXB	2.5	JR-4300-0	10	55	P4	695 1100	Triode No. 1
3D6	2.5	JR-6230-0	37	74	P4	1325 2100	Triode No. 2
3E6	3.0	JR-6234-0	15	67	P4	1010 1600	
3LE4	2.5	JR-6237-4	55	55	P4	695 1100	
3LF4	2.5	JR-6230-0	30	72	P4	1200 1900	Short on 3
4X150A	6.3	JT-6721-0	48	85	P4	2400 3800	USE STARK TYPE 4X150A ADAPTER
5X3	5.0	JR-0300-0	0	13	P3*		CONNECT LEAD TO RADIATOR
5X3	5.0	JR-0200-0	0	13	P3*		Plate No. 1
5Z3	5.0	JR-0300-0	0	49	P3*		Plate No. 2
5Z3	5.0	JR-0200-0	0	43	P3*		Plate No. 1
6A3	6.3	JR-3200-0	67	82	P4	1890 3000	Plate No. 2
6A4	6.3	JR-3240-0	28	73	P4	1260 2000	
6A6	6.3	JR-5604-0	12	65	P4	945 1500	Triode No. 1
6A6	6.3	JR-3204-0	12	65	P4	945 1500	Triode No. 2
6A7	6.3	JR-0236-5	22	50	P4	630 1000	Pent. Sect. Cap = G
6A7	6.3	JR-5436-2	30	73	P4	300	Osc. Sect.
6AB5/6N5	6.3	JR-5403-0	0	0	P4		HIKORPHOS ONLY
6AB5/6N5	6.3	JR-5423-0	0	0	P4		OK OVER 240 ON 3000 SCALE
6B5	6.3	JR-4235-0	0	63	P4	945 1500	Eye Open

6B7	6.3	JR-0236-0	30	50	P4	630 1000	Pent. Sect. Cap = G
6B7	6.3	JR-0536-0	30	0	P1*		Diode No. 1
6B7	6.3	JR-0436-0	30	0	P1*		Diode No. 2
6C6	6.3	JR-5307-0	21	73	P4	1260 2000	
6C6	6.3	JR-0235-4	21	60	P4	770 1225	Cap = G
6C7	6.3	JR-0206-0	29	60	P4	790 1250	Cap = G
6C7	6.3	JR-0506-0	29	0	P1*		Triode Sect.
6C7	6.3	JR-0406-0	29	0	P1*		Diode No. 1
6C85	7.5	JR-4023-0	49	87	P4	2835 4500	Diode No. 2
6D6	6.3	JR-0235-4	21	68	P4	1010 1600	Cap = P
6D7	6.3	JR-0236-4	24	58	P4	770 1225	Cap = G
6E5	6.3	JR-5403-0			P4		Eye Open
6E5	6.3	JR-5423-0			P4		Eye Closed
6E6	6.3	JR-5604-0	54	63	P4	880 1400	Triode No. 1
6E6	6.3	JR-3204-0	54	63	P4	880 1400	Triode No. 2
6E7	6.3	JR-0236-4	24	67	P4	945 1500	Cap = G
6F4	6.3	JR-2306-0	30	92	P4	3780 6000	
6F7	6.3	JR-0236-5	28	55	P4	695 1100	Pent. Sect. Cap = G
6F7	6.3	JR-5436-2	28	0	P4	315 500	Triode Sect.
6H5	6.3	JR-5403-0			P4		Eye Open
6H5	6.3	JR-5423-0			P4		Eye Closed
6L4	6.3	JR-2306-0	34	81	P4	1890 3000	
6N5	6.3	JR-5403-0			P4		Eye Open
6N5	6.3	JR-5423-0			P4		Eye Closed
6T5	6.3	JR-5403-0			P4		Eye Open
6T5	6.3	JR-5423-0			P4		Eye Closed
6U5	6.3	JR-5403-0			P4		Eye Open
6U5	6.3	JR-5423-0			P4		Eye Closed
6Y5	6.3	JR-0504-0	0	30	P3*		Plate No. 1
6Y5	6.3	JR-0304-0	0	30	P3*		Plate No. 2
6Z3	6.3	JR-0203-0	0	35	P3*		
6Z4	6.3	JR-0304-0	0	35	P3*		Plate No. 1
6Z4	6.3	JR-0204-0	0	35	P3*		Plate No. 2
6Z5	12.6	JS-0504-0	0	49	P3*		Plate No. 1
6Z5	12.6	JS-0304-0	0	49	P3*		Plate No. 2
7A4	6.3	JR-6207-0	23	73	P4	1260 2000	
7A5	6.3	JR-6237-0	28	87	P4	3780 6000	
7A6	6.3	JR-0607-5	0	49	P1*		Diode No. 1
7A6	6.3	JR-0302-5	0	49	P1*		Diode No. 2
7A7	6.3	JR-6237-4	27	71	P4	1190 1750	
7A8	6.3	JR-6257-4	20	50	P4	630 1000	Ampl. Sect.
7A8	6.3	JR-4357-6	20	0	P4	315 500	Osc. Sect.
7AB7	6.3	HS-5314-0	10	71	P4	1135 1800	
7AD7	6.3	JR-6237-4	10	90	P4	3905 6200	
7AF7	6.3	JR-5607-0	21	79	P4	1640 2600	Triode No. 1
7AF7	6.3	JR-4302-0	21	79	P4	1640 2600	Triode No. 2
7AG7	6.3	JR-6237-4	0	82	P4	1890 3000	
7AH7	6.3	JR-6237-4	0	83	P4	2080 3300	
7AJ7	6.3	JR-6237-4	9	76	P4	1435 2275	
7AK7	6.3	JR-6237-4	0	85	P4	2670 4000	
7AX7	6.3	JR-6237-4	0	85	P4	2520 4000	
7B4	6.3	JR-6207-0	12	52	P4	630 1000	

7B5	6.3	JR-6237-0	34	68	P4 1010 1600	
7B6	6.3	JR-3207-0	11	34	P4 470 750	Triode Sect.
7B6	6.3	JR-0607-2	11	0	P1*	Diode No. 1
7B6	6.3	JR-0507-2	11	0	P1*	Diode No. 2
7B7	6.3	JR-6237-4	27	70	P4 1070 1700	
7B8	6.3	JR-6257-4	18	67	P4 945 1500	Pent. Sect.
7B8	6.3	JR-4357-6	18	30	P4 410 650	Osc. Sect.
7C4	6.3	JR-0407-0	0	30	P1*	Diode
7C5	6.3	JR-6237-0	30	82	P4 1890 3000	
7C6	6.3	JR-3207-0	10	18	P4 390 600	Triode Sect.
7C6	6.3	JR-0607-2	10	0	P1*	Diode No. 1
7C6	6.3	JR-0507-2	10	0	P1*	Diode No. 2
7C7	6.3	JR-6237-4	22	60	P4 820 1300	
7E5	6.3	JS-1304-0	15	82	P4 1890 3000	
7E6	6.3	JR-3207-0	18	72	P4 1200 1900	Triode Sect.
7E6	6.3	JR-0607-2	18	0	P1*	Diode No. 1
7E6	6.3	JR-0507-2	18	0	P1*	Diode No. 2
7E7	6.3	JR-6257-0	22	60	P4 820 1300	Pent. Sect.
7E7	6.3	JR-0407-2	22	0	P1*	Diode No. 1
7E7	6.3	JR-0307-2	22	0	P1*	Diode No. 2
7F7	6.3	JR-5607-3	0	60	P4 820 1300	Triode No. 1
7F7	6.3	JR-4302-6	0	60	P4 820 1300	Triode No. 2
7F8	6.3	HS-8605-0	10	86	P4 2520 4000	Triode No. 1
7F8	6.3	HS-1304-0	10	86	P4 2520 4000	Triode No. 2
7G7	6.3	JR-6237-4	18	73	P4 1260 2000	
7G8	6.3	JR-5736-2	10	74	P4 1325 2100	Tetrode No. 1
7G8	6.3	JR-4236-7	10	74	P4 1325 2100	Tetrode No. 2
7H7	6.3	JR-6237-4	10	82	P4 1890 3000	
7J7	6.3	JR-6257-4	18	38	P4 505 800	Heptode Sect.
7J7	6.3	JR-4357-6	18	51	P4 630 1000	Triode Sect.
7K7	6.3	JR-4302-0	0	50	P4 630 1000	Triode Sect.
7K7	6.3	JR-0507-0	0	0	P1*	Diode No. 1
7K7	6.3	JR-0607-0	0	0	P1*	Diode No. 2
7L7	6.3	JR-6237-4	12	73	P4 1260 2000	
7N7	6.3	JR-5607-3	23	73	P4 1260 2000	Triode No. 1
7N7	6.3	JR-4302-6	23	73	P4 1260 2000	Triode No. 2
7Q7	6.3	JR-6237-4	21	0	P4 315 500	Ampl. Sect.
7Q7	6.3	JR-4237-6	21	40	P4 505 800	Osc. Sect.
7R7	6.3	JR-6257-0	10	82	P4 1890 3000	Pent. Sect.
7R7	6.3	JR-0407-2	10	0	P1*	Diode No. 1
7R7	6.3	JR-0307-2	10	0	P1*	Diode No. 2
7S7	6.3	JR-6257-4	18	65	P4 945 1500	Heptode Sect.
7S7	6.3	JR-4357-6	0	65	P4 945 1500	Triode Sect.
7T7	6.3	JR-6237-4	9	82	P4 1890 3000	
7V7	6.3	JR-6237-4	6	86	P4 2520 4000	
7W7	6.3	JR-6237-5	11	82	P4 1890 3000	
7X6	6.3	JR-0607-5	0	55	P3*	Plate No. 1
7X6	6.3	JR-0302-5	0	55	P3*	Plate No. 2
7X7	6.3	JR-3204-0	0	37	P4 570 900	Triode Sect.
7X7	6.3	JR-0504-0	0	61	P1*	Diode No. 1
7X7	6.3	JR-0607-0	0	61	P1*	Diode No. 2
7Y4	6.3	JR-0607-0	0	33	P3*	Plate No. 1
7Y4	6.3	JR-0307-0	0	33	P3*	Plate No. 2

7Z4	6.3	JR-0607-0	0	24	P3*	Plate No. 1
7Z4	6.3	JR-0307-0	0	24	P3*	Plate No. 2
10	7.5	JR-3200-0	39	61	P4 790 1250	
10Y	7.5	JR-3200-0	12	65	P4 945 1500	
12A	5.0	JR-3200-0	44	70	P4 1040 1650	
12A5	12.6	JR-4235-0	51	71	P4 1135 1800	
12A7	12.6	JR-0236-5	48	48	P4 615 975	Pent. Sect. Cap = G
12A7	12.6	JR-0504-2	0	40	P3*	Rect. Sect.
12B7	12.6	JR-6237-4	22	72	P4 1200 1900	
12Z3	12.6	JR-0203-0	0	35	P3*	
12Z5	12.6	JR-0605-0	0	40	P3*	Plate No. 1
12Z5	12.6	JR-0203-0	0	40	P3*	Plate No. 2
14A4	12.6	JR-6207-0	17	81	P4 1640 2600	
14A5	12.6	JR-6237-0	12	82	P4 1890 3000	
14A7	12.6	JR-6237-4	22	72	P4 1200 1900	
14AF7	12.6	JR-5607-0	0	78	P4 1575 2500	
14AF7	12.6	JR-4302-0	0	78	P4 1575 2500	
14B6	12.6	JR-3207-0	0	54	P4 695 1100	
14B6	12.6	JR-0607-2	0	0	P1*	Diode No. 1
14B6	12.6	JR-0507-2	0	0	P1*	Diode No. 2
14B8	12.6	JR-6257-4	27	49	P4 630 1000	Pent. Sect.
14B8	12.6	JR-4357-6	18	0	P4 315 500	Usc. Sect. UK over 240
14C5	12.6	JR-6237-0	23	84	P4 2330 3700	
14C7	12.6	JR-6237-4	11	77	P4 1430 2275	
14E6	12.6	JR-3207-0	12	71	P4 1135 1800	Triode Sect.
14E6	12.6	JR-0607-2	12	0	P1*	Diode No. 1
14E6	12.6	JR-0507-2	12	0	P1*	Diode No. 2
14E7	12.6	JR-6257-0	24	61	P4 820 1300	Pent. Sect.
14E7	12.6	JR-0407-2	24	0	P1*	Diode No. 1
14E7	12.6	JR-0307-2	24	0	P1*	Diode No. 2
14F7	12.6	JR-5607-3	0	68	P4 1010 1600	Triode No. 1
14F7	12.6	JR-4302-6	0	68	P4 1010 1600	Triode No. 2
14F8	12.6	HS-8605-0	10	86	P4 2520 4000	Triode No. 1
14F8	12.6	HS-1304-0	10	86	P4 2520 4000	Triode No. 2
14H7	12.6	JR-6237-4	10	82	P4 1890 3000	
14J7	12.6	JR-6257-4	18	38	P4 505 800	Heptode Sect.
14J7	12.6	JR-4357-6	18	51	P4 630 1000	Triode Sect.
14N7	12.6	JR-5607-3	23	73	P4 1260 2000	Triode No. 1
14N7	12.6	JR-4302-6	23	73	P4 1260 2000	Triode No. 2
14Q7	12.6	JR-6237-4	21	0	P4 315 500	Pent. Sect.
14Q7	12.6	JR-4237-6	21	40	P4 505 800	Osc. Sect.
14R7	12.6	JR-6257-0	10	82	P4 1890 3000	Pent. Sect.
14R7	12.6	JR-0407-2	10	0	P1*	Diode No. 1
14R7	12.6	JR-0307-2	10	0	P1*	Diode No. 2
14S7	12.6	JR-6257-4	18	65	P4 945 1500	Heptode Sect.
14S7	12.6	JR-4357-6	0	65	P4 945 1500	Triode Sect.
14V7	12.6	JR-6237-4	6	86	P4 2520 4000	
14W7	12.6	JR-6237-5	11	82	P4 1890 3000	
14Y7	12.6	JR-3204-0	0	37	P4 570 900	Triode Section
14X7	12.6	JR-0504-0	0	61	P1*	Diode No. 1
14X7	12.6	JR-0607-0	0	61	P1*	Diode No. 2
14Y4	12.6	JR-0607-0	0	33	P3*	Plate No. 1
14Y4	12.6	JR-0307-0	0	33	P3*	Plate No. 2
14Z3	12.6	JR-0203-0	0	43	P3*	

15	2.0	JR-0234-0	22	19	P4 395	625	Cap = G
15A6	12.6	EV-2713-6	11	91	P4 4725	7500	
18	14.0	JR-4235-0	29	73	P4 1260	2000	
19	2.0	JR-4500-0	15	51	P4 630	1000	Triode No. 1
19	2.0	JR-3200-0	15	51	P4 630	1000	Triode No. 2
RK20A	7.5	JR-3024-0	0	78	P4 1575	2500	Cap = P
22	3.0	JR-0230-0	45	0	P4 315	500	Cap = G
24A	2.5	JR-0234-0	12	51	P4 630	1000	Cap = G
VT25A	7.5	JR-3200-0	30	73	P4 1260	2000	
25B5	25.0	JR-4235-0	0	78	P4 1575	2500	
25T	6.3	JR-3000-0	0	50	P4 630	1000	Cap = P
25Y5	25.0	JR-0504-0	0	40	P3 *		Plate No. 1
25Y5	25.0	JR-0203-0	0	40	P3 *		Plate No. 2
25Z3	25.0	JR-0203-0	0	49	P3 *		
25Z5	25.0	JR-0504-0	0	40	P3 *		Plate No. 1
25Z5	25.0	JR-0203-0	0	40	P3 *		Plate No. 2
25Z5MG	25.0	JR-0507-0	0	40	P3 *		Plate No. 1
25Z5MG	25.0	JR-0304-0	0	40	P3 *		Plate No. 2
26	1.5	JR-3200-0	43	56	P4 725	1150	
27	2.5	JR-3204-0	41	49	P4 630	1000	
28D7	25.0	JR-7536-2	17	87	P4 2520	4000	Pentode No. 1
28D7	25.0	JR-2436-7	17	87	P4 2520	4000	Pentode No. 2
30	2.0	JR-3200-0	40	44	P4 570	900	
31	2.0	JR-3200-0	65	43	P4 580	925	
32	2.0	JR-0230-0	37	23	P4 405	640	Cap = G
33	2.0	JR-3240-0	35	61	P4 915	1450	
RK33	6.3	JR-4506-0	38	62	P4 865	1375	Triode No. 1
RK33	6.3	JR-0302-0	38	62	P4 865	1375	Triode No. 2
34	2.0	JR-0230-0	33	17	P4 380	600	Cap = G
35	2.5	JR-0234-0	24	51	P4 645	1020	Cap = G
35A5	35.0	JR-6237-0	33	90	P4 3720	5900	Cap = G
35Y4	BLST	JR-0247-0					Short on 1-2-3-4-5
35Y4	35.0	JR-0207-0	0	55	P3 *		Rect. Sect.
35Z3	35.0	JR-0207-0	0	60	P3 *		
36	6.3	JR-0234-0	24	52	P4 660	1050	Cap = G
37	6.3	JR-3204-0	41	44	P4 570	900	
38	6.3	JR-0234-0	39	50	P4 660	1050	Cap = G
39/44	6.3	JR-0234-0	28	50	P4 630	1000	Cap = G
40	5.0	JR-3200-0	32	73	P4	200	MICROMHOS ONLY OK OVER 160 ON 3000 SCALE
41	6.3	JR-4235-0	34	67	P4 1010	1600	
42	6.3	JR-4235-0	29	73	P4 1260	2000	
43	25.0	JR-4235-0	43	76	P4 1450	2300	
45	2.5	JR-3200-0	61	72	P4 1165	1850	
46	2.5	JR-3240-0	30	73	P4 1260	2000	
47	2.5	JR-3240-0	22	73	P4 1260	2000	
48	25.0	JR-4235-0	58	73	P4 1260	2000	
49	2.0	JR-3240-0	49	55	P4 770	1225	
50	7.5	JR-3200-0	61	65	P4 945	1500	
50A5	50.0	JR-6237-0	30	91	P4 4725	7500	
50X6	50.0	JR-0607-5	0	55	P3 *		Plate No. 1
50X6	50.0	JR-0302-5	0	55	P3 *		Plate No. 2

HD-51		KR-0302-0	0	0	P2 *		
51/51S	2.5	JR-0234-0	24	51	P4 645	1020	Cap = G
52	6.3	JR-3240-0	33	77	P4 1510	2400	
53	2.5	JR-5604-2	12	65	P4 945	1500	Triode No. 1
53	2.5	JR-3204-6	12	65	P4 945	1500	Triode No. 2
55	2.5	JR-0205-0	39	49	P4 615	975	Triode Sect. Cap = G
55	2.5	JR-0405-0	39	0	P1 *		DIODE NO. 1 OK OVER 500 ON 3000 SCALE
55	2.5	JR-0305-0	39	0	P1 *		DIODE NO. 2 OK OVER 500 ON 3000 SCALE
56	2.5	JR-3204-0	29	65	P4 915	1450	
57	2.5	JR-0235-4	21	58	P4 770	1225	Cap = G
57A	6.3	JR-0235-4	21	58	P4 770	1225	Cap = G
58	2.5	JR-0235-4	24	66	P4 915	1450	Cap = G
58A/58AS	6.3	JR-0235-4	24	66	P4 915	1450	Cap = G
59	2.5	JR-4236-5	22	73	P4 1260	2000	
HY-65	6.3	JR-5040-7	0	82	P4 1890	3000	Cap = P
VT-67	2.0	JR-3200-0	40	44	P4 570	900	
HY-69	6.3	JR-3024-0	0	82	P4 1890	3000	Cap = P
71A	5.0	JR-3200-0	73	68	P4 1040	1650	
75	6.3	JR-0205-0	11	34	P4 470	750	Triode Sect. Cap = G
75	6.3	JR-0405-2	11	0	P1 *		Diode No. 1
75	6.3	JR-0305-2	11	0	P1 *		Diode No. 2
75MG	6.3	JR-0407-0	11	34	P4 470	750	Triode Sect. Cap = G
75MG	6.3	JR-0507-0	11	0	P1 *		Diode No. 1
75MG	6.3	JR-0607-0	11	0	P1 *		Diode No. 2
76	6.3	JR-3204-0	29	65	P4 915	1450	
77	6.3	JR-0235-4	21	58	P4 770	1225	Cap = G
78	6.3	JR-0235-4	24	66	P4 915	1450	Cap = G
79	6.3	JR-0504-0	15	48	P4 630	1000	Triode No. 1 Cap = G
79	6.3	JR-3204-0	15	48	P4 630	1000	Triode No. 2
80	5.0	JR-0300-0	0	20	P3 *		Plate No. 1
80	5.0	JR-0200-0	0	15	P3 *		Plate No. 2
81	7.5	JR-0200-0	0	6	P1 *		
82	2.5	JR-0300-0	0	67	P3 *		Plate No. 1
82	2.5	JR-0200-0	0	61	P3 *		Plate No. 2
C82-B	5.0	JR-3200-0	46	83	P4 630	1000	
83	5.0	JR-0300-0	0	70	P3 *		Plate No. 1
83	5.0	JR-0200-0	0	65	P3 *		Plate No. 2
C83	5.0	JR-3200-0	79	65	P4 945	1500	
83V	5.0	JR-0300-0	0	60	P3 *		Plate No. 1
83V	5.0	JR-0200-0	0	60	P3 *		Plate No. 2
84	6.3	JR-0304-0	0	35	P3 *		Plate No. 1
84	6.3	JR-0204-0	0	35	P3 *		Plate No. 2
85	6.3	JR-0205-0	39	49	P4 615	975	Triode Sect. Cap = G
85	6.3	JR-0405-2	39	0	P1 *		Diode No. 1
85	6.3	JR-0305-2	39	0	P1 *		Diode No. 2
85AS	6.3	JR-0205-0	28	52	P4 695	1100	Cap = G, Triode Sect.
85AS	6.3	JR-0405-2	28	0	P1 *		Diode No. 1
85AS	6.3	JR-0305-2	28	0	P1 *		Diode No. 2
89/89Y	6.3	JR-0235-4	37	66	P4 975	1550	Cap = G
99	3.0	JR-3200-0	55	73	P4	425	MICROMHOS ONLY OK OVER 340 ON 3000 SCALE
99X	3.0	HR-8600-0	55	73	P4	425	MICROMHOS ONLY OK OVER 340 ON 3000 SCALE
112A	5.0	JR-3200-0	44	70	P4 1040	1650	

WESTERN ELECTRIC TUBES

101D	4.3	JR-3200-0	55	53	P4 732	1100	
101F,J,L,M	4.3	JR-3200-0	53	53	P4 732	1100	
102D	2.0	JR-3200-0	25	0	P4 335	500	
102F	2.0	JR-3200-0	25	12	P4 385	580	
104D	4.3	JR-3200-0	75	53	P4 732	1100	
CK-108	6.3	JR-0235-4	21	58	P4 608	1225	Cap = G
CK-113	50.0	JR-5347-6	48	71	P4 1135	1800	Pent. Sect.
CK-113	50.0	JR-0602-0	0	50	P3*		Rect. Sect.
205D,E,F	5.0	JR-3200-0	34	65	P4 965	1450	RAYONET PIN IS OVER GRID. USE AN ADAPTER
231D	3.0	JR-3200-0	49	6	P4 356	540	
244A	2.0	JR-3204-0	42	42	P4 600	900	
245A	2.0	JR-0234-0	55	29	P4 482	725	Cap = G
247A	2.0	JR-3204-0	33	14	P4 614	920	
TS-251	50.0	JR-5347-6	50	70	P4 1200	1800	Pent. Sect.
TS-251	50.0	JR-0602-3	0	50	P3*		Rect. Sect.
257A	3.0	JR-0200-0	49	6	P4 294	540	Cap = G
259A,B	2.0	JR-0234-0	33	48	P4 732	1100	Cap = G
262A, B	10.0	JR-0203-0	31	49	P4 660	1000	Cap = G
264-B	1.5	JR-3200-0	49	13	P4 385	580	
264C	1.5	JR-3200-0	54	12	P4 385	580	
271A	5.0	JR-3204-0	32	81	P4 1940	2900	
272A	10.0	JR-3204-0	51	38	P4 635	950	
274A	5.0	JR-0200-0	0	20	P3*		Plate No. 1
274A	5.0	JR-0300-0	0	20	P3*		Plate No. 2
274B	5.0	HR-0600-0	0	20	P3*		Plate No. 1
274B	5.0	HR-0400-0	0	20	P3*		Plate No. 2
275A	5.0	JR-3200-0	68	79	P4 1800	2700	
283A	2.0	JR-0234-0	28	56	P4 800	1200	Cap = G
285A	2.0	JR-0230-4	40	42	P4 600	900	Cap = G
300A,B	5.0	JR-3200-0	60	87	P4 3060	4600	
307A	5.0	JR-3020-4	32	78	P4 1660	2500	Cap = P
309A	10.0	JR-0234-0	31	42	P4 600	900	Cap = G
310A,B	10.0	JR-0235-4	26	57	P4 800	1200	Cap = G
311A	10.0	JR-0234-0	38	77	P4 1600	2400	Cap = G
313C		AP-0201-8	0	83	P5*		
313CA		AP-8201-0	0	80	P5*		
328A	7.5	JR-0235-4	16	69	P4 1165	1750	Cap = G
329A	7.5	JR-0234-0	38	78	P4 1635	2450	Cap = G
336A	10.0	JR-4235-0	24	82	P4 2065	3100	
337A	10.0	JR-0235-4	30	49	P4 1140	1700	Cap = G
339A	5.0	JR-3024-0	0	82	P4 2140	3200	Cap = P
348A	6.3	JR-0347-5	13	70	P4 1200	1800	Cap = G
349A	6.3	JR-5347-0	17	86	P4 2640	4000	
350A	6.3	JR-3024-0	15	90	P4 4265	6400	Cap = P
350B	6.3	JR-5347-0	25	90	P4 4165	6250	
351A	6.3	JR-0507-2	0	50	P3*		Plate No. 1
351A	6.3	JR-0307-2	0	50	P3*		Plate No. 2

352A	10.0	JR-0205-0	36	24	P4 435	650	Cap = G Triode Sect.
352A	10.0	JR-0405-0	0	21	P1*		Diode No. 1
352A	10.0	JR-0305-0	0	22	P1*		Diode No. 2
367A	6.3	JV-6147-0	24	90	P4 4000	6000	
373A	2.0	JR-4760-3	13	48	P4 660	1000	
374A	3.0	JR-4760-3	38	79	P4 1800	2700	
375A	20.0	JR-5347-0	53	84	P4 2460	3700	
381A	6.3	HR-0502-0	0	60	P1*		
383A	6.3	HR-4602-0	28	73	P4 1320	2000	
385A	6.3	HR-5032-8	10	78	P4 1650	2500	Cap = P
387A	6.3	HR-5032-8	20	73	P4 1320	2000	Cap = P
393A	2.5	JR-4000-0	#	0	P2*		Cap = P
396A	6.3	KR-7608-2	13	88	P4 3340	5300	Strikes at about 28
396A	6.3	KR-3402-8	13	88	P4 3340	5300	Triode No. 1
398A/							Triode No. 2
5603	6.3	JR-4760-3	37	87	P4 3590	5300	
399A	1.1	DX-6210-0	24	53	P4 695	1100	
400A	1.1	DX-6218-5	35	0	P4 265	500	Pent. Sect. Short on 2
400A	1.1	DX-8216-5	35	0	P4 265	500	Osc. Sect. Short on 2
401A/							
5590	6.3	JR-3567-0	30	73	P4 1335	2000	
403A	6.3	JR-3562-0	24	65	P4 1000	1500	
403B	6.3	JR-3567-2	0	86	P4 2705	4300	
404A	6.3	KT-1684-0	13	90	P4 4000	6000	
407A	20.0	KV-7608-2	13	88	P4 3530	5300	Triode No. 1
407A	20.0	BV-3402-8	13	88	P4 3530	5300	Triode No. 2
408A	20.0	JR-3562-0	24	65	P4 1000	1500	
409A	6.3	JR-3562-7	14	70	P4 1150	1750	
412A	6.3	EV-0907-3	0	65	P3*		Plate No. 1
412A	6.3	EV-0103-7	0	65	P3*		Plate No. 2
417A	6.3	DZ-5106-0	27	90	P4 4000	6000	
420	2.5	JR-0300-0	0	70	P3*		Plate No. 1
420	2.5	JR-0200-0	0	70	P3*		Plate No. 2
420A/							
5755	12.6	EV-6807-3	0	48	P4 660	1000	Triode No. 1
420A/							
5755	12.6	EV-3102-6	0	48	P4 660	1000	Triode No. 2
421A/							
5998	6.3	JX-4506-1	56	92	P4 5280	8000	Triode No. 1
421A/							
5998	6.3	JX-2103-5	56	92	P4 5280	8000	Triode No. 2
422A	5.0	HR-0600-0	0	68	P3*		Plate No. 1
422A	5.0	HR-0400-0	0	68	P3*		Plate No. 2
429A	20.0	BW-8254-0	24	88	P4 3020	4800	USE STARK TYPE 429A ADAPTER

6F32	6.3	BY-0342-5	6	75	P4	1890	3000	Cap = G USE STARK TYPE "EG" ADAPTER
12E1	6.3	BY-5047-0	60	85	P4	2640	4000	Cap = P Cap = P OK ABOVE DIODE OK USE STARK "EG" ADAPTER USE STARK "EG" ADAPTER
19H1	4.3	JR-0000-0	----	30	P3*	-----		
63SPT	6.3	KR-7326-4	20	70	P4	1260	2000	
85A2	----	AP-0102-0	0	75	P5*	-----		
150B2	OFF	AP-0302-0	0	10	P5*	-----		
A1834	6.3	JX-2103-0	70	95	P4	2900	4300	Reads in Green Triode No. 1 Triode No. 2 ALLOW SUFFICIENT TIME TO WARM UP BEFORE TEST. THEN CHECK QUICKLY. VERY HIGH DRAIN TUBE
A1834	6.3	JX-4506-0	70	95	P4	2900	4300	
AZ31	4.3	HR-0400-0	0	0	P3*	-----		Plate No. 1. MAKE LINE TEST AT 1300 ON 3000 SCALE
AZ31	4.3	HR-0600-0	0	0	P3	-----		Plate No. 2 MAKE LINE TEST AT 1300 ON 3000 SCALE
B65	6.3	JX-4506-1	23	73	P4	1260	2000	Triode No. 1
B65	6.3	JX-2103-5	23	73	P4	1260	2000	Triode No. 2 MAKE LINE TEST AT 1300 ON 3000 SCALE. TEST FOR MAZDA MAN. ONLY. USE STARK "EA" ADAPTER PLACE RED DOT LEAD ON TOP PIN
D1	4.3	JR-0703-0	0	0	P1*	-----		
DA90	1.5	HT-0201-0	0	0	P1*	-----		
DAF91	1.5	DX-6580-0	34	11	P4	330	525	Pent Sect.
DAF91	1.5	DX-0180-0	34	0	P1*	-----		Diode Sect.
DAF96	1.5	DX-6583-0	0	0	P4	315	500	Pent Sect. AVERAGE ENGLISH READING 1000 ON 3000 SCALE
DAF96	1.5	DX-0103-0	0	0	P1*	-----		Diode Sect. OK ABOVE DIODES OK
DCC90	3.0	DX-5600-0	32	73	P4	1260	2000	Triode No. 1
DCC90	3.0	DX-1200-0	22	73	P4	1260	2000	Triode No. 2
DF91	1.5	DX-6210-0	34	34	P4	470	750	
DH77	6.3	JR-3702-0	18	57	P4	755	1200	Triode Sect.
DH77	6.3	JR-3602-0	18	0	P1*	-----		Diode No. 1
DH77	6.3	JR-3502-0	18	0	P1*	-----		Diode No. 2
DK91	1.5	DX-8106-2	60	42	P4	570	900	
DK92	1.5	DX-8616-0	33	0	P4	380	600	
DK96	1.5	DX-8256-7	Use this setting for short check only					
DK96	1.5	DX-8617-0	0	43	P4	630	1000	
DL92	2.5	HT-1280-0	43	61	P4	820	1300	
DL93	2.5	DX-8210-0	33	73	P4	1260	2000	
DL94	3.0	DX-6210-0	31	68	P4	1040	1650	
DL95	2.5	JR-5340-0	38	71	P4	1135	1800	
DL96	2.5	DX-6210-0	44	53	P4	695	1100	
DLS-15-								
ZV1825	4.3	JR-0203-0	0	0	-----			USE STARK "EB" ADAPTER MAKE LINE TEST AT 1300 ON 3000 SCALE. SET SHORT SWITCH TO POSITION 5 BEFORE TESTING
WITH GOOD TUBE SHORT INDICATOR WILL LIGHT AND SHOW SHORT ON ALL POSITIONS 30 TO 50 SECONDS AFTER INSERTING TUBE AND APPLYING POWER								
EA50	6.3	JR-0703-0	0	52	P1*	-----		USE STARK "EA" ADAPTER. PLACE RED DOT LEAD ON TOP PIN.
EA91	6.3	JR-3562-0	27	79	P4	1730	2750	
EAB80	6.3	EV-8907-0	16	49	P4	630	1000	Triode Sect.

EABC80	6.3	EV-0607-0	16	0	P1*		Diode No. 1 OK ABOVE DIODES OK
EABC80	6.3	EV-0107-0	16	53	P1*		Diode No. 2
EABC80	6.3	EV-0203-0	16	53	P1*		Diode No. 3
EAC91	6.3	JR-6705-0	19	73	P4	1485 2350	Triode Sect.
EAC91	6.3	JR-0302-0	0	53	P1*		Diode Sect.
EB91	6.3	JR-0703-0	0	53	P1*		Diode No. 1
EB91	6.3	JR-0205-0	0	19	P1*		Diode No. 2
EBC90	6.3	JR-3702-0	18	57	P4	755 1200	Triode Sect.
EBC90	6.3	JR-3602-0	18	0	P1*		Diode No. 1
EBC90	6.3	JR-3502-0	18	0	P1*		Diode No. 2
EBC91	6.3	JR-3702-5	12	58	P4	790 1250	Triode Sect.
EBC91	6.3	JR-3602-5	0	0	P1*		Diode No. 1
EBC91	6.3	JR-3502-7	0	0	P1*		Diode No. 2
EBF80	6.3	EV-2613-9	17	75	P4	1385 2200	Pent Sect.
EBF80	6.3	EV-2713-9	0	0	P1*		Diode No. 1
EBF80	6.3	EV-2813-9	0	0	P1*		Diode No. 2
EC52	6.3	BZ-2403-0	15	83	P4	2330 3700	USE STARK "EG" ADAPTER USE STARK "EA" ADAPTER, PLACE LEADS ON TWO PINS, LINE UP RED DOTS.
EC53	6.3	JR-5703-0	18	70	P4	1260 2000	Shorts on 1-2-3-5
EC80	6.3	EV-1903-0	12	86	P4	3150 5000	
EC81	6.3	EV-1803-0	23	84	P4	2520 4000	
EC92	6.3	JR-6307-0	9	83	P4	2508 3800	
ECC40	6.3	JR-6302-5	28	60	P4	880 1400	Triode No. 1
ECC40	6.3	JR-5407-1	28	56	P4	820 1300	Triode No. 2 USE STARK TYPE EL42 ADAPTER
ECC81	12.6	EV-7608-0	10	86	P4	2520 4000	Triode No. 1
ECC81	12.6	EV-2103-0	10	86	P4	2520 4000	Triode No. 2
ECC82	12.6	EV-7608-0	24	75	P4	1385 2200	Triode No. 1
ECC82	12.6	EV-2103-0	24	75	P4	1385 2200	Triode No. 2
ECC83	12.6	EV-7608-0	12	58	P4	790 1250	Triode No. 1
ECC83	12.6	EV-2103-0	12	58	P4	790 1250	Triode No. 2
ECC85	6.3	EV-7608-0	11	85	P4	2580 4100	Triode No. 1
ECC85	6.3	EV-2103-0	11	85	P4	2580 4100	Triode No. 2
ECC91	6.3	JR-5207-0	20	81	P4	1890 3000	Triode No. 1
ECC91	6.3	JR-6307-0	20	81	P4	1890 3000	Triode No. 2
ECH42/ 6CU7	6.3	JR-5347-2	20	69	P4	1135 1800	Hexode Sect.
ECH42/ 6CU7	6.3	JR-2607-5	30	0	P4	400	TRIODE SECT. ENGLISH READING OK ABOVE 1000 ON 3000 SCALE. USE STARK TYPE EL42 ADAPTER
ECH81	6.3	EV-2613-7	14	70	P4	1260 2000	Heptode Sect.
ECH81	6.3	EV-9803-0	14	80	P4	2000 3200	Triode Sect.
ECL80	6.3	EV-9683-7	24	80	P4	1765 2800	Pent. Sect.
ECL80	6.3	EV-2103-0	35	35	P4	505 800	Triode Sect.
EF36	6.3	JR-0347-5	22	57	P4	770 1225	Cap = G
EF42	6.3	JR-5347-2	13	78	P4	1700 2700	USE STARK TYPE EL42 ADAPTER
EF50	6.3	BZ-7326-4	20	70	P4	1260 2000	USE STARK "EG" ADAPTER
EF54	6.3	BZ-6238-0	13	88	P4	1890 3000	USE STARK "EG" ADAPTER
EF55	6.3	BZ-7326-4	18	87	P4	4410 7000	USE STARK "EG" ADAPTER
EF80	6.3	EV-2781-9	13	81	P4	1890 3000	
EF85	6.3	EV-2783-9	11	80	P4	1890 3000	
EF86	6.3	EX-9613-8	10	68	P4	1130 1800	

EF89	6.3	EV-2783-9	23	73	P4 1320 2000																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																													
------	-----	-----------	----	----	--------------	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

EVERYTHING 4 LESS



ENJOY YOUR BOOKS



PLEASE VISIT OUR STORE FOR EVEN MORE GREAT STUFF!

WWW.EVERYTHING4LESSSTORE.COM

COPYRIGHT NOTICE

ALL MATERIALS INCLUDING CD/DVD AND PDF FILES ARE COPYRIGHTED

WWW.EVERYTHING4LESSSTORE.COM VON WALTHOUR PRODUCTIONS AND MAY NOT BE REPRODUCED, COPIED OR RESOLD UNDER ANY CIRCUMSTANCES. YOU MAY HOWEVER MAKE A COPY FOR YOUR OWN PERSONAL BACKUP. MATERIALS ARE FOR PERSONAL USE ONLY.

IF YOU PURCHASED THIS FROM ANYWHERE BUT FROM US PLEASE NOTIFY US IMMEDIATELY SO THAT WE MAY CHECK IF YOU PURCHASED FROM AN AUTHORIZED RESELLER SO WE CAN LET YOU KNOW IF YOU NEED TO RETURN FOR FULL REFUND FROM AN UNAUTHORIZED SELLER.

THANKS AGAIN AND PLEASE TAKE THE TIME TO VISIT OUR STORE.

ATTENTION! EVERYTHING ON SALE NOW!!



HOT SALE!

**THIS PAGE COPYRIGHT VON WALTHOUR PRODUCTIONS
WWW.EVERYTHING4LESSSTORE.COM**